

DIGITAL RPM METERS

MODEL : PE 6050



TECHNICAL SPECIFICATIONS

Range	: 0-9999 RPM
Display	: 4 digit 0.5"ht red LED
Resolution	: 1 RPM
Accuracy	: 0.05% ± 1 count. Input : From Technogenerator, Magnetic pickup, Infra red sensors, photo-encoders/ switches, proximity switches.
Power	: 230 V AC ± 10%, 50Hz.
Dimensions	: 96(W) x 96(H) x 40(D)mm ³
Weight	: 1.5kg.
Options	: 1. scale division facility by Rotary switch for 2 to 10 2. Available in Panel Mounting size of 96mm(W) x 48mm(H) x 110mm(D) 3. Fractional RPM measurement/low RPM measurement. 4. Linear Speed measurement.

PREMIER ELECTROSYSTEMS

3 & 204A, Planet Industrial Estate, Subhash Rd, Vile Parle (East), Mumbai : 400 057, INDIA

TEL : +91 22 2616 99 23 / +91 22 2616 99 24

E MAIL : feedback@premierin.com WEBSITE: www.premierin.com

DIGITAL RPM MONITOR

MODEL : PE 6060



(With High & Low Limit tripping)

TECHNICAL SPECIFICATIONS

Range	: 0-9999 RPM
Display	: 4 digit 0.5"ht red LED
Resolution	: 1 RPM
Accuracy	: 0.05% \pm 1 count. Input : From Technogenerator, Magnetic pickup, Infra red sensors, photo-encoders/ switches, proximity switches.
Setpoints	: Two nos. : 'HIGH' and 'LOW' both continuously adjustable by means of 4 digit thumb wheel switches.
Output	: One change over relay contact, 2A/230 AC, for each setting.
Power	: 230 V AC \pm 10%, 50Hz.
Dimensions	: 96(W) x 96(H) x 150(D)mm ³
Weight	: 2.5kg.
Options	: 1. RPM Monitor with one limit setting. 2. Zero speed switches.

PREMIER ELECTROSYSTEMS

3 & 204A, Planet Industrial Estate, Subhash Rd, Vile Parle (East), Mumbai : 400 057, INDIA

TEL : +91 22 2616 99 23 / +91 22 2616 99 24

E MAIL : feedback@premierin.com WEBSITE: www.premierin.com