

DIGITAL ENDURANCE TESTER

MODEL: PE 930M



- To carry out Life Test of any appliance – To set ON Time , OFF Time and no of times the cycle is repeated
- Facilities : Start/Stop buttons, Battery backup for memory retention
- Provision to connect Multiple load up to 25 Amp directly

TECHNICAL SPECIFICATION

A. Counter Section

- Display : 6 digit, 0.5" ht red LED for Counter
- Range : 0 -- 999999
- Resolution : 1 Count
- Set Point : One No adjustable by Membrane Key Board
- Reset : Push button Switch to reset – provided

B. Timer Section.

- Display : 4 digit, 0.5"ht red LED.
- Range : 0-9999 Min for ON and OFF Time
- Resolution : 1 min.
- Accuracy : 0.05 % +/- 1 count
- Set Point : Two No, On Time and Off Time – both independently adjustable by membrane Key Board
- Reset : Push button Switch to reset – provided
- Power : 230 V AC +/-10%, 50 Hz

PREMIER ELECTROSYSTEMS

3 & 204A, Planet Industrial Estate, Subhash Rd, Vile Parle (East), Mumbai : 400 057, INDIA

TEL : +91 22 2616 99 23 / +91 22 2616 99 24

E MAIL : feedback@premierin.com WEBSITE: www.premierin.com